

APPLICATION FOR LOW VOLTAGE DIRECTIVE

On Behalf of

SHENZHEN WEIDAYUAN TECHNOLOGY CO., LTD.

Adapter

Model: WDY-XXXYYYYY

**(XXX=030-300 indicates rated output voltage range 3.0-30.0V;
YYYYY=00200-12000 indicates rated output current range 200-12000mA)**

Prepared For : SHENZHEN WEIDAYUAN TECHNOLOGY CO., LTD.
5/F, C Building, Jinshan Industrial Park, No. 52 Road 2,
Dalangshan, Wanfeng, Shajing Town, Baoan District,
Shenzhen, China
Tel: (86)755-36673062
Fax: (86)755-61125883

Prepared By : Anbotek Compliance Laboratory Limited
1/F, 1/Building, SEC Industrial Park, No.4 Qianhai Road,
Nanshan District, Shenzhen, 518054, China
Tel: (86)755-26066544
Fax: (86)755-26014772

Date of Test: Aug. 10, 2012 to Aug. 17, 2012
Date of Report: Aug. 17, 2012
Report Number: 201208661S

TEST REPORT EN 60950-1 Information technology equipment – Safety – Part 1: General requirements	
Reference No.....	201208661S
Compiled by (+ signature).....	Phevos Hu / Project Engineer <i>Phevos Hu</i>
Approved by (+ signature).....	Terry Tian / Deputy Manager <i>Terry Tian</i>
Date of issue.....	Aug. 17, 2012
Contents.....	54 pages (including 3 photo pages)
Testing laboratory	
Name.....	Anbotek Compliance Laboratory Limited
Address.....	1/F, 1/Building, SEC Industrial Park, No.4 Qianhai Road, Nanshan District, Shenzhen, 518054, China
Testing location.....	Same as above
Client	
Name.....	SHENZHEN WEIDAYUAN TECHNOLOGY CO., LTD.
Address.....	5/F, C Building, Jinshan Industrial Park, No. 52 Road 2, Dalangshan, Wanfeng, Shajing Town, Baoan District, Shenzhen, China
Test specification	
Standard	EN 60950-1:2006+A11:2009+A1:2010+A12:2011
Test procedure	Compliance with EN 60950-1:2006+A11:2009+A1:2010+A12:2011
Procedure deviation.....	N.A.
Non-standard test method.....	N.A.
Test item	
Description.....	Adapter
Trademark.....	N.A.
Model and/or type reference	WDY-XXXYYYYY (XXX=030-300 indicates rated output voltage range 3.0-30.0V; YYYYY=00200-12000 indicates rated output current range 200-12000mA)
Manufacturer.....	SHENZHEN WEIDAYUAN TECHNOLOGY CO., LTD.
Address.....	5/F, C Building, Jinshan Industrial Park, No. 52 Road 2, Dalangshan, Wanfeng, Shajing Town, Baoan District, Shenzhen, China
Rating(s)	Input: 100-240V~, 50/60Hz, 2A Output: (for details see attachment)

Test item particulars	
Equipment mobility	<input checked="" type="checkbox"/> Movable <input type="checkbox"/> Hand-held <input type="checkbox"/> Transportable <input type="checkbox"/> Stationary <input type="checkbox"/> For building-in <input type="checkbox"/> Direct plug-in
Connection to the mains.....	<input checked="" type="checkbox"/> Pluggable equipment <input checked="" type="checkbox"/> Type A <input type="checkbox"/> Type B <input type="checkbox"/> Permanent connection <input type="checkbox"/> Detachable power supply cord <input type="checkbox"/> Non-detachable power supply cord <input type="checkbox"/> Not directly connected to the mains <input type="checkbox"/> built-in component, consider in end system
Operating condition	<input checked="" type="checkbox"/> Continuous <input type="checkbox"/> Rated operating / resting time:
Over voltage category (OVC)	<input type="checkbox"/> OVC I <input checked="" type="checkbox"/> OVC II <input type="checkbox"/> OVC III <input type="checkbox"/> OVC IV <input type="checkbox"/> Other:
Mains supply tolerance (%) or absolute mains supply values	+10/-10 %
Tested for IT power systems	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No
IT testing, phase-phase voltage (V)	N.A.
Class of equipment	<input checked="" type="checkbox"/> Class I <input type="checkbox"/> Class II <input type="checkbox"/> Class III <input type="checkbox"/> Not classified
Considered current rating of protective device as part of the building installation (A)	16
Pollution degree (PD)	<input type="checkbox"/> PD 1 <input checked="" type="checkbox"/> PD 2 <input type="checkbox"/> PD 3
IP protection class	IPX0
Altitude during operation (m)	2000
Altitude of test laboratory (m)	<500
Mass of equipment (kg)	0.542
Possible test case verdicts	
- test case does not apply to the test object	N (N.A.)
- test object does meet the requirement	P (Pass)
- test object does not meet the requirement.....	F (Fail)
Testing	
Date of receipt of test item	Aug. 10, 2012
Date(s) of performance of tests.....	Aug. 10, 2012 to Aug. 17, 2012
General remarks	
This test report shall not be reproduced except in full without the written approval of the testing laboratory.	
The test results presented in this report relate only to the item tested.	
"(see remark #)" refers to a remark appended to the report.	
"(see appended table)" refers to a table appended to the report.	
Throughout this report a point is used as the decimal separator.	

General product information

1. Clearance was evaluated for altitude up to 2000m above sea level.
2. The maximum operating temperature is 40°C.
3. This series contains many models. All the test were performed on model: WDY-12010000. The selected model for test are the most representative, if no specified, the model was the selected for test.

Copy of marking plate(s)

Adapter

Model: WDY-12010000

Input: 100-240V~, 50/60Hz, 2A

Output: 12V --- , 10A



**SHENZHEN WEIDAYUAN TECHNOLOGY CO.,
LTD.**

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
1	GENERAL		P
1.5	Components		P
1.5.1	General	See below	P
	Comply with IEC 60950-1 or relevant component standard	Components which were found to affect safety aspects comply with the requirements of this standards of the relevant IEC/EN component standards (see appended table 1.5.1)	P
1.5.2	Evaluation and testing of components	Components that are certified to IEC and/or national standards are used correctly within their ratings Components not covered by IEC standards are tested under the conditions present in the equipment	P
1.5.3	Thermal controls	No such thermal control	N
1.5.4	Transformers	See annex C	P
1.5.5	Interconnecting cables		N
1.5.6	Capacitors bridging insulation	X,Y-cap, IEC60384-14 approved	P
1.5.7	Resistors bridging insulation	Bleeder resistor	P
1.5.7.1	Resistors bridging functional, basic or supplementary insulation		P
1.5.7.2	Resistors bridging double or reinforced insulation between a.c. mains and other circuits		N
1.5.7.3	Resistors bridging double or reinforced insulation between a.c. mains and antenna or coaxial cable		N
1.5.8	Components in equipment for IT power systems	No applied for.	N
1.5.9	Surge suppressors		N
1.5.9.1	General		N
1.5.9.2	Protection of VDRs		N
1.5.9.3	Bridging of functional insulation by a VDR		N
1.5.9.4	Bridging of basic insulation by a VDR	(see appended table 1.5.1)	N
1.5.9.5	Bridging of supplementary, double or reinforced insulation by a VDR		N
1.6	Power interface		P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
1.6.1	AC power distribution systems	TN, TT power distribution systems	P
1.6.2	Input current	(see appended table 1.6.2)	P
1.6.3	Voltage limit of hand-held equipment	Not a hand-held equipment	N
1.6.4	Neutral conductor	Basic insulation provided	P
1.7	Marking and instructions		P
1.7.1	Power rating		P
	Rated voltage(s) or voltage range(s) (V)..... :	100-240V~	P
	Symbol for nature of supply, for d.c. only..... :		N
	Rated frequency or rated frequency range (Hz) .. :	50/60	P
	Rated current (mA or A)..... :	2.0A	P
	Manufacturer's name or trade-mark or identification mark	SHENZHEN WEIDAYUAN TECHNOLOGY CO., LTD.	P
	Model identification or type reference	WDY-12010000	P
	Symbol for Class II equipment only		N
	Other markings and symbols		N
1.7.2	Safety instructions and marking	Installation instruction provided	P
1.7.2.1	General		P
1.7.2.2	Disconnect devices	External circuit breaker shall be provide by user	N
1.7.2.3	Overcurrent protective device	Evaluated on the approve SMPS (see appended table 1.5.1)	P
1.7.2.4	IT power distribution systems		N
1.7.2.5	Operator access with a tool		N
1.2.7.6	Ozone		N
1.7.3	Short duty cycles	Continuous operation	N
1.7.4	Supply voltage adjustment	No such device	N
	Methods and means of adjustment; reference to installation instructions		N
1.7.5	Power outlets on the equipment	No such device	N
1.7.6	Fuse identification (marking, special fusing characteristics, cross-reference)	"F1 T5.0A 250VAC" marked on PCB near fuse	P
1.7.7	Wiring terminals		P
1.7.7.1	Protective earthing and bonding terminals	Protective bonding terminals only	P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
1.7.7.2	Terminals for a.c. mains supply conductors		N
1.7.7.3	Terminals for d.c. mains supply conductors		N
1.7.8	Controls and indicators		P
1.7.8.1	Identification, location and marking	The function of controls affecting safety is obvious regardless of language	P
1.7.8.2	Colours		N
1.7.8.3	Symbols according to IEC 60417.....		N
1.7.8.4	Markings using figures		N
1.7.9	Isolation of multiple power sources	There is only one connection to hazardous voltages	N
1.7.10	Thermostats and other regulating devices	No such regulating devices	N
1.7.11	Durability	Rubbing test for 15 s with water then for 15 s with petroleum spirit	P
1.7.12	Removable parts	No such part	N
1.7.13	Replaceable batteries	No battery used	N
	Language(s)		--
1.7.14	Equipment for restricted access locations		N

2	PROTECTION FROM HAZARDS		P
2.1	Protection from electric shock and energy hazards		P
2.1.1	Protection in operator access areas		P
2.1.1.1	Access to energized parts		P
	Test by inspection		P
	Test with test finger (Figure 2A)		P
	Test with test pin (Figure 2B)		P
	Test with test probe (Figure 2C)		N
2.1.1.2	Battery compartments		N
2.1.1.3	Access to ELV wiring	No internal wiring at ELV	N
	Working voltage (V _{peak} or V _{rms}); minimum distance through insulation (mm)	(see appended table 2.10.5)	--
2.1.1.4	Access to hazardous voltage circuit wiring	No hazardous voltage wiring in operator accessible area	N
2.1.1.5	Energy hazards	(see appended table table 2.1.1.5 c) 1)	P
2.1.1.6	Manual controls		N
2.1.1.7	Discharge of capacitors in equipment		P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
	Measured voltage (V); time-constant (s)	76V after 1s; Limit: 325Vx37%=120V	--
2.1.1.8	Energy hazards – d.c. mains supply		N
	a) Capacitor connected to the d.c. mains supply ..		N
	b) Internal battery connected to the d.c. mains supply		N
2.1.1.9	Audio amplifiers		N
2.1.2	Protection in service access areas		N
2.1.3	Protection in restricted access locations		N

2.2	SELV circuits		P
2.2.1	General requirements	See below	P
2.2.2	Voltages under normal conditions (V)	42.4V peak or 60Vd.c. was not exceeded in SELV circuit under normal operation	P
2.2.3	Voltages under fault conditions (V)	Under fault conditions voltages never exceed 71 V peak and 120 V dc and do not exceed 42.4 V peak or 60 V dc for more than 0.2 sec	P
2.2.4	Connection of SELV circuits to other circuits	Output only designed to be connected to SELV circuits of other equipment	P

2.3	TNV circuits		N
2.3.1	Limits	No TNV circuit	N
	Type of TNV circuits		--
2.3.2	Separation from other circuits and from accessible parts		N
2.3.2.1	General requirements		N
2.3.2.2	Protection by basic insulation		N
2.3.2.3	Protection by earthing		N
2.3.2.4	Protection by other constructions		N
2.3.3	Separation from hazardous voltages		N
	Insulation employed.....		--
2.3.4	Connection of TNV circuits to other circuits		N
	Insulation employed.....		--
2.3.5	Test for operating voltages generated externally		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
2.4	Limited current circuits		P
2.4.1	General requirements		P
2.4.2	Limit values		P
	Frequency (Hz)	60	--
	Measured current (mA)	0.11	--
	Measured voltage (V).....	264	--
	Measured circuit capacitance (nF or μ F)		--
2.4.3	Connection of limited current circuits to other circuits		N

2.5	Limited power sources		P
	a) Inherently limited output		N
	b) Impedance limited output		N
	c) Regulating network limited output under normal operating and single fault condition		P
	d) Overcurrent protective device limited output		N
	Max. Output voltage (V), max. Output current (A), max. apparent power (VA).....	(see appended table 2.5)	--
	Current rating of overcurrent protective device (A):		--
	Use of integrated circuit (IC) current limiters		--

2.6	Provisions for earthing and bonding		P
2.6.1	Protective earthing	Metal enclosure was earthed	P
2.6.2	Functional earthing		N
2.6.3	Protective earthing and protective bonding conductors		P
2.6.3.1	General		P
2.6.3.2	Size of protective earthing conductors	No provided	N
	Rated current (A), cross-sectional area (mm^2), AWG		--
2.6.3.3	Size of protective bonding conductors		P
	Rated current (A), cross-sectional area (mm^2), AWG	Protective bonding conductors comply with 2.6.3.4	--
	Protective current rating (A), cross-sectional area (mm^2), AWG		--
2.6.3.4	Resistance of earthing conductors and their terminations; resistance (Ω), voltage drop (V), test current (A), duration (min)	Resistance: 9.8m Ω ; Test current: 32A for 2min	P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
2.6.3.5	Colour of insulation	Protective bonding conductors are green with yellow stripe	P
2.6.4	Terminals		P
2.6.4.1	General		P
2.6.4.2	Protective earthing and bonding terminals		p
	Rated current (A), type, nominal thread diameter (mm)		--
2.6.4.3	Separation of the protective earthing conductor from protective bonding conductors		P
2.6.5	Integrity of protective earthing		P
2.6.5.1	Interconnection of equipment		n
2.6.5.2	Components in protective earthing conductors and protective bonding conductors		P
2.6.5.3	Disconnection of protective earth	Approved AC inlet used	P
2.6.5.4	Parts that can be removed by an operator		P
2.6.5.5	Parts removed during servicing		P
2.6.5.6	Corrosion resistance	No risk of corrosion. Complies with Annex J	P
2.6.5.7	Screws for protective bonding		N
2.6.5.8	Reliance on telecommunication network or cable distribution system	No TNV circuit	N

2.7	Overcurrent and earth fault protection in primary circuits		P
2.7.1	Basic requirements	Fuse F1 used as an integral part of the equipment	P
	Instructions when protection relies on building installation		N
2.7.2	Faults not simulated in 5.3.7		P
2.7.3	Short-circuit backup protection	The building installation is considered as provide as providing short-circuit backup protection	P
2.7.4	Number and location of protective devices		P
2.7.5	Protection by several devices		N
2.7.6	Warning to service personnel.....		N

2.8	Safety interlocks		N
2.8.1	General principles		N
2.8.2	Protection requirements		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
2.8.3	Inadvertent reactivation		N
2.8.4	Fail-safe operation		N
	Protection against extreme hazard		N
2.8.5	Moving parts		N
2.8.6	Overriding		N
2.8.7	Switches, relays and their related circuits		N
2.8.7.1	Separation distances for contact gaps and their related circuit (mm)		N
2.8.7.2	Overload test		N
2.8.7.3	Endurance test		N
2.8.7.4	Electric strength test		N
2.8.8	Mechanical actuators		N

2.9	Electrical insulation		P
2.9.1	Properties of insulating materials	Natural rubber, asbestos and hygroscopic material are not used as insulation	P
2.9.2	Humidity conditioning	48h	P
	Relative humidity (%), temperature (°C)	93%, 30°C	--
2.9.3	Grade of insulation		P
2.9.4	Separation from hazardous voltages		P
	Method(s) used	Method 1) and 3)	--

2.10	Clearances, creepage distances and distances through insulation		P
2.10.1	General		P
2.10.1.1	Frequency	50/60	P
2.10.1.2	Pollution degrees	2	P
2.10.1.3	Reduced values for functional insulation		N
2.10.1.4	Intervening unconnected conductive parts		N
2.10.1.5	Insulation with varying dimensions		N
2.10.1.6	Special separation requirements		N
2.10.1.7	Insulation in circuits generating starting pulses		N
2.10.2	Determination of working voltage		P
2.10.2.1	General		P
2.10.2.2	RMS working voltage		P
2.10.2.3	Peak working voltage		P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
2.10.3	Clearances	Altitude up to 2000m above sea level	P
2.10.3.1	General	Annex F and minimum clearances considered.	P
2.10.3.2	Mains transient voltages		P
	a) AC mains supply	2500Vpeak	P
	b) Earthed d.c. mains supplies		N
	c) Unearthed d.c. mains supplies		N
	d) Battery operation		N
2.10.3.3	Clearances in primary circuits	(see appended table 2.10.3 and 2.10.4)	P
2.10.3.4	Clearances in secondary circuits		N
2.10.3.5	Clearances in circuits having starting pulses		N
2.10.3.6	Transients from a.c. mains supply		N
2.10.3.7	Transients from d.c. mains supply		N
2.10.3.8	Transients from telecommunication networks and cable distribution systems		N
2.10.3.9	Measurement of transient voltage levels		N
	a) Transients from a mains supply		N
	For an a.c. mains supply		N
	For a d.c. mains supply		N
	b) Transients from a telecommunication network :		N
2.10.4	Creepage distances		P
2.10.4.1	General		P
2.10.4.2	Material group and comparative tracking index		P
	CTI tests	Assumed as material group IIIa and IIIb	--
2.10.4.3	Minimum creepage distances	(see appended table 2.10.3 and 2.10.4)	P
2.10.5	Solid insulation		P
2.10.5.1	General		P
2.10.5.2	Distances through insulation	(see appended table 2.10.5)	P
2.10.5.3	Insulating compound as solid insulation		N
2.10.5.4	Semiconductor devices		P
2.10.5.5	Cemented joints		N
2.10.5.6	Thin sheet material		P
2.10.5.7	Separable thin sheet material		P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
	Number of layers (pcs)..... :	3	--
2.10.5.8	Non-separable thin sheet material		N
2.10.5.9	Thin sheet material – standard test procedure		N
	Electric strength test		--
2.10.5.10	Thin sheet material – alternative test procedure	(see appended table 2.10.5)	N
	Electric strength test		--
2.10.5.11	Insulation in wound components		N
2.10.5.12	Wire in wound components		P
	Working voltage		P
	a) Basic insulation not under stress		N
	b) Basic, supplementary, reinforced insulation		N
	c) Compliance with Annex U		P
	Two wires in contact inside wound component; angle between 45° and 90°		P
2.10.5.13	Wire with solvent-based enamel in wound components		N
	Electric strength test		--
	Routine test		N
2.10.5.14	Additional insulation in wound components		N
	Working voltage		N
	- Basic insulation not under stress		N
	- Supplementary, reinforced insulation		N
2.10.6	Construction of printed boards		P
2.10.6.1	Uncoated printed boards		P
2.10.6.2	Coated printed boards		N
2.10.6.3	Insulation between conductors on the same inner surface of a printed board		N
2.10.6.4	Insulation between conductors on different layers of a printed board		N
	Distance through insulation		N
	Number of insulation layers (pcs)		N
2.10.7	Component external terminations		N
2.10.8	Tests on coated printed boards and coated components		N
2.10.8.1	Sample preparation and preliminary inspection		N
2.10.8.2	Thermal conditioning		N
2.10.8.3	Electric strength test		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
2.10.8.4	Abrasion resistance test		N
2.10.9	Thermal cycling		N
2.10.10	Test for Pollution Degree 1 environment and insulating compound		N
2.10.11	Tests for semiconductor devices and cemented joints		N
2.10.12	Enclosed and sealed parts		N

3	WIRING, CONNECTIONS AND SUPPLY		P
3.1	General		P
3.1.1	Current rating and overcurrent protection	All internal wires are UL recognized wiring which is PVC insulated, rated VW-1. Internal wiring gauge is suitable for current intended to be carried	P
3.1.2	Protection against mechanical damage	Wires do not touch sharp edge and heat sinks which could damage the insulation and cause hazard	P
3.1.3	Securing of internal wiring	The wires are secured by soldering, solder pins and quick connect terminals so that a loosening of the terminal connection is unlikely	P
3.1.4	Insulation of conductors		P
3.1.5	Beads and ceramic insulators	Not used	N
3.1.6	Screws for electrical contact pressure	No screws for electrical contact pressure	N
3.1.7	Insulating materials in electrical connections	Contact pressure is not transmitted through insulating material	P
3.1.8	Self-tapping and spaced thread screws	No self-tapping screws are used for connection purposes	N
3.1.9	Termination of conductors	All terminations are fixed reliable	P
	10 N pull test	Complied	P
3.1.10	Sleeving on wiring	No sleeves used as supplementary insulation	N
3.2	Connection to a mains supply		P
3.2.1	Means of connection	The unit is provided with appliance inlet	P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
3.2.1.1	Connection to an a.c. mains supply		P
3.2.1.2	Connection to a d.c. mains supply		N
3.2.2	Multiple supply connections	Only one supply	N
3.2.3	Permanently connected equipment	Not a permanently connected equipment	N
	Number of conductors, diameter of cable and conduits (mm)		--
3.2.4	Appliance inlets		N
3.2.5	Power supply cords		N
3.2.5.1	AC power supply cords		N
	Type		--
	Rated current (A), cross-sectional area (mm ²), AWG		--
3.2.5.2	DC power supply cords		N
3.2.6	Cord anchorages and strain relief		N
	Mass of equipment (kg), pull (N)		--
	Longitudinal displacement (mm)		--
3.2.7	Protection against mechanical damage		N
3.2.8	Cord guards		N
	Diameter or minor dimension D (mm); test mass (g)		--
	Radius of curvature of cord (mm)		--
3.2.9	Supply wiring space		N
3.3	Wiring terminals for connection of external conductors		N
3.3.1	Wiring terminals		N
3.3.2	Connection of non-detachable power supply cords		N
3.3.3	Screw terminals		N
3.3.4	Conductor sizes to be connected		N
	Rated current (A), cord/cable type, cross-sectional area (mm ²)		--
3.3.5	Wiring terminal sizes		N
	Rated current (A), type, nominal thread diameter (mm)		--
3.3.6	Wiring terminal design		N
3.3.7	Grouping of wiring terminals		N
3.3.8	Stranded wire		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict

3.4	Disconnection from the mains supply		P
3.4.1	General requirement	Circuit breaker shall be provided when in filed installation and play as disconnect device	P
3.4.2	Disconnect devices	Approved AC inlet used	P
3.4.3	Permanently connected equipment		N
3.4.4	Parts which remain energized		N
3.4.5	Switches in flexible cords		N
3.4.6	Number of poles – single-phase and d.c. equipment		P
3.4.7	Number of poles – three-phase equipment		N
3.4.8	Switches as disconnect devices		N
3.4.9	Plugs as disconnect devices		N
3.4.10	Interconnected equipment		N
3.4.11	Multiple power sources		N

3.5	Interconnection of equipment		P
3.5.1	General requirements	See below	P
3.5.2	Types of interconnection circuits	Connect to SELV circuits	P
3.5.3	ELV circuits as interconnection circuits	No ELV interconnection circuit	N
3.5.4	Data ports for additional equipment		N

4	PHYSICAL REQUIREMENTS		P
4.1	Stability		N
	Angle of 10°	Weight less than 7.0kg	N
	Test force (N)	Equipment is not a floor standing unit	N

4.2	Mechanical strength		P
4.2.1	General		P
4.2.2	Steady force test, 10 N	10N force applied to components and parts other than parts serving as an enclosure, no hazard	P
4.2.3	Steady force test, 30 N		N
4.2.4	Steady force test, 250 N		P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
4.2.5	Impact test		P
	Fall test		N
	Swing test		N
4.2.6	Drop test; height (mm)	1m	P
4.2.7	Stress relief test	100°C for 7 hours	P
4.2.8	Cathode ray tubes		N
	Picture tube separately certified		N
4.2.9	High pressure lamps		N
4.2.10	Wall or ceiling mounted equipment; force (N)		N
4.2.11	Rotating solid media		N
	Test to cover on the door		N

4.3	Design and construction		P
4.3.1	Edges and corners	All edges and corners are judged to sufficiently well rounded so as not to constitute a hazard	P
4.3.2	Handles and manual controls; force (N)		N
4.3.3	Adjustable controls	No such control device	N
4.3.4	Securing of parts	Electrical and mechanical connections can be expected to withstand usual mechanical stress	P
4.3.5	Connection by plugs and sockets		P
4.3.6	Direct plug-in equipment	Not direct plug-in type	N
	Torque		--
	Compliance with the relevant mains plug standard		N
4.3.7	Heating elements in earthed equipment	No heating elements provided	N
4.3.8	Batteries		N
	- Overcharging of a rechargeable battery		N
	- Unintentional charging of a non-rechargeable battery		N
	- Reverse charging of a rechargeable battery		N
	- Excessive discharging rate for any battery		N
4.3.9	Oil and grease	No oil and grease	N
4.3.10	Dust, powders, liquids and gases	The equipment in intended use not considered to be	N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
		exposed to dust, powers , liquids and gases	
4.3.11	Containers for liquids or gases	No container for liquid or gas	N
4.3.12	Flammable liquids	No flammable liquid	N
	Quantity of liquid (l)		N
	Flash point (°C)		N
4.3.13	Radiation		P
4.3.13.1	General		P
4.3.13.2	Ionizing radiation		N
	Measured radiation (pA/kg)		--
	Measured high-voltage (kV)		--
	Measured focus voltage (kV)		--
	CRT markings		--
4.3.13.3	Effect of ultraviolet (UV) radiation on materials	No ultraviolet radiation	N
	Part, property, retention after test, flammability classification		N
4.3.13.4	Human exposure to ultraviolet (UV) radiation		N
4.3.13.5	Lasers (including laser diodes) and LEDs		P
4.3.13.5.1	Lasers (including laser laser diodes)		P
	Laser class	Class I	--
4.3.13.5.2	Light emitting diodes (LEDs)		N
4.3.13.6	Other types		N

4.4	Protection against hazardous moving parts		N
4.4.1	General	No moving parts	N
4.4.2	Protection in operator access areas		N
	Household and home/office document/media shredders	(see Annex EE)	N
4.4.3	Protection in restricted access locations		N
4.4.4	Protection in service access areas		N
4.4.5	Protection against moving fan blades		N
4.4.5.1	General		N
	Not considered to cause pain or injury. a)		N
	Is considered to cause pain, not injury. b)		N
	Considered to cause injury. c)		N
4.4.5.2	Protection for users		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict

	Use of symbol or warning		N
4.4.5.3	Protection for service persons		N
	Use of symbol or warning		N

4.5	Thermal requirements		P
4.5.1	General		P
4.5.2	Temperature tests		P
	Normal load condition per Annex L	Rated load with continuous operation	--
4.5.3	Temperature limits for materials	(see appended table 4.5)	P
4.5.4	Touch temperature limits	(see appended table 4.5)	P
4.5.5	Resistance to abnormal heat	(see appended table 4.5.5)	N

4.6	Openings in enclosures		N
4.6.1	Top and side openings		N
	Dimensions (mm)		--
4.6.2	Bottoms of fire enclosures		N
	Construction of the bottom, dimensions (mm) ..		--
4.6.3	Doors or covers in fire enclosures		N
4.6.4	Openings in transportable equipment		N
4.6.4.1	Constructional design measures		N
	Dimensions (mm)		--
4.6.4.2	Evaluation measures for larger openings		N
4.6.4.3	Use of metallized parts		N
4.6.5	Adhesives for constructional purposes		N
	Conditioning temperature (°C), time (weeks).....		--

4.7	Resistance to fire		P
4.7.1	Reducing the risk of ignition and spread of flame	Use of materials with the required flammability classes	P
	Method 1, selection and application of components wiring and materials	Selection and application of components and materials which minimize the possibility of ignition and spread of flame	P
	Method 2, application of all of simulated fault condition tests		N
4.7.2	Conditions for a fire enclosure		P
4.7.2.1	Parts requiring a fire enclosure		P

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
4.7.2.2	Parts not requiring a fire enclosure		N
4.7.3	Materials		P
4.7.3.1	General	PCB: V-1 Min.	P
4.7.3.2	Materials for fire enclosures	Enclosure: V-0	P
4.7.3.3	Materials for components and other parts outside fire enclosures		N
4.7.3.4	Materials for components and other parts inside fire enclosures	Min. V-2	P
4.7.3.5	Materials for air filter assemblies	No air filter provided	N
4.7.3.6	Materials used in high-voltage components	< 4kV	N

5	ELECTRICAL REQUIREMENTS AND SIMULATED ABNORMAL CONDITIONS		P
5.1	Touch current and protective conductor current		P
5.1.1	General		P
5.1.2	Configuration of equipment under test (EUT)		P
5.1.2.1	Single connection to an a.c. mains supply		P
5.1.2.2	Redundant multiple connections to an a.c. mains supply		N
5.1.2.3	Simultaneous multiple connections to an a.c. mains supply		N
5.1.3	Test circuit		P
5.1.4	Application of measuring instrument		P
5.1.5	Test procedure		P
5.1.6	Test measurements		P
	Supply voltage (V)	264V, 60Hz	--
	Measured touch current (mA)	(see appended table 5.1.6)	--
	Max. allowed touch current (mA)		--
	Measured protective conductor current (mA)		--
	Max. allowed protective conductor current (mA) . :		--
5.1.7	Equipment with touch current exceeding 3,5 mA		N
5.1.7.1	General		N
5.1.7.2	Simultaneous multiple connections to the supply		N
5.1.8	Touch currents to telecommunication networks and cable distribution systems and from telecommunication networks		N
5.1.8.1	Limitation of the touch current to a telecommunication network or to a cable distribution system		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
	Supply voltage (V)		--
	Measured touch current (mA)		--
	Max. allowed touch current (mA)		--
5.1.8.2	Summation of touch currents from telecommunication networks		N
	a) EUT with earthed telecommunication ports		N
	b) EUT whose telecommunication ports have no reference to protective earth		N

5.2	Electric strength		P
5.2.1	General	(see appended table 5.2)	P
5.2.2	Test procedure	(see appended table 5.2)	P

5.3	Abnormal operating and fault conditions		P
5.3.1	Protection against overload and abnormal operation	(See appended table 5.3)	P
5.3.2	Motors	(see appended Annex B)	N
5.3.3	Transformers	(see appended Annex C)	P
5.3.4	Functional insulation	Method c) used	P
5.3.5	Electromechanical components	No electromechanical component	N
5.3.6	Audio amplifiers in ITE		N
5.3.7	Simulation of faults		P
5.3.8	Unattended equipment		N
5.3.9	Compliance criteria for abnormal operating and fault conditions	No fire occurred. Electric strength tests passed after all fault tested	P
5.3.9.1	During the tests		P
5.3.9.2	After the tests		P

6	CONNECTION TO TELECOMMUNICATION NETWORKS		N
6.1	Protection of telecommunication network service persons, and users of other equipment connected to the network, from hazards in the equipment		N
6.1.1	Protection from hazardous voltages		N
6.1.2	Separation of the telecommunication network from earth		N
6.1.2.1	Requirements		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
	Supply voltage (V)		--
	Current in the test circuit (mA)		--
6.1.2.2	Exclusions		N
6.2	Protection of equipment users from overvoltages on telecommunication networks		N
6.2.1	Separation requirements		N
6.2.2	Electric strength test procedure		N
6.2.2.1	Impulse test		N
6.2.2.2	Steady-state test		N
6.2.2.3	Compliance criteria		N
6.3	Protection of the telecommunication wiring system from overheating		N
	Max. output current (A)		--
	Current limiting method		--
7	CONNECTION TO CABLE DISTRIBUTION SYSTEMS		N
7.1	General		N
7.2	Protection of cable distribution system service persons, and users of other equipment connected to the system, from hazardous voltages in the equipment		N
7.3	Protection of equipment users from overvoltages on the cable distribution system		N
7.4	Insulation between primary circuits and cable distribution systems		N
7.4.1	General		N
7.4.2	Voltage surge test		N
7.4.3	Impulse test		N
A	ANNEX A, TESTS FOR RESISTANCE TO HEAT AND FIRE		N
A.1	Flammability test for fire enclosures of movable equipment having a total mass exceeding 18 kg, and of stationary equipment (see 4.7.3.2)		N
A.1.1	Samples		--
	Wall thickness (mm).....		--
A.1.2	Conditioning of samples; temperature (°C)		N
A.1.3	Mounting of samples		N
A.1.4	Test flame (see IEC 60695-11-3)		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
	Flame A, B, C or D		--
A.1.5	Test procedure		N
A.1.6	Compliance criteria		N
	Sample 1 burning time (s).....		--
	Sample 2 burning time (s).....		--
	Sample 3 burning time (s).....		--
A.2	Flammability test for fire enclosures of movable equipment having a total mass not exceeding 18 kg, and for material and components located inside fire enclosures (see 4.7.3.2 and 4.7.3.4)		N
A.2.1	Samples, material		--
	Wall thickness (mm).....		--
A.2.2	Conditioning of samples; temperature (°C)		N
A.2.3	Mounting of samples		N
A.2.4	Test flame (see IEC 60695-11-4)		N
	Flame A, B or C		--
A.2.5	Test procedure		N
A.2.6	Compliance criteria		N
	Sample 1 burning time (s).....		--
	Sample 2 burning time (s).....		--
	Sample 3 burning time (s).....		--
A.2.7	Alternative test acc. To IEC 60695-11-5, cl. 5 and 9		N
	Sample 1 burning time (s).....		--
	Sample 2 burning time (s).....		--
	Sample 3 burning time (s).....		--
A.3	Hot flaming oil test (see 4.6.2)		N
A.3.1	Mounting of samples		N
A.3.2	Test procedure		N
A.3.3	Compliance criterion		N

B	ANNEX B, MOTOR TESTS UNDER ABNORMAL CONDITIONS (see 4.7.2.2 and 5.3.2)		N
B.1	General requirements		N
	Position		--
	Manufacturer		--
	Type		--
	Rated values		--

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
B.2	Test conditions		N
B.3	Maximum temperatures		N
B.4	Running overload test		N
B.5	Locked-rotor overload test		N
	Test duration (days)		--
	Electric strength test: test voltage (V)		--
B.6	Running overload test for d.c. motors in secondary circuits		N
B.6.1	General		N
B.6.2	Test procedure		N
B.6.3	Alternative test procedure		N
B.6.4	Electric strength test; test voltage (V)		N
B.7	Locked-rotor overload test for d.c. motors in secondary circuits		N
B.7.1	General		N
B.7.2	Test procedure		N
B.7.3	Alternative test procedure		N
B.7.4	Electric strength test; test voltage (V)		N
B.8	Test for motors with capacitors		N
B.9	Test for three-phase motors		N
B.10	Test for series motors		N
	Operating voltage (V)		--

C	ANNEX C, TRANSFORMERS (see 1.5.4 and 5.3.3)		P
	Position	T1	--
	Manufacturer	(see appended table 1.5.1)	--
	Type	(see appended table 1.5.1)	--
	Rated values	(see appended table 1.5.1)	--
	Method of protection		--
C.1	Overload test	(see appended table 5.3)	P
C.2	Insulation	(see appended table 5.2)	P
	Protection from displacement of windings	By bobbin and insulation tape	P

D	ANNEX D, MEASURING INSTRUMENTS FOR TOUCH-CURRENT TESTS (see 5.1.4)		P
D.1	Measuring instrument		P
D.2	Alternative measuring instrument		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict

E	ANNEX E, TEMPERATURE RISE OF A WINDING (see 1.4.13)		N
----------	--	--	---

F	ANNEX F, MEASUREMENT OF CLEARANCES AND CREEPAGE DISTANCES (see 2.10 and Annex G)		P
----------	---	--	---

G	ANNEX G, ALTERNATIVE METHOD FOR DETERMINING MINIMUM CLEARANCES		N
G.1	Clearances		N
G.1.1	General		N
G.1.2	Summary of the procedure for determining minimum clearances		N
G.2	Determination of mains transient voltage (V)		N
G.2.1	AC mains supply		N
G.2.2	Earthed d.c. mains supplies		N
G.2.3	Unearthed d.c. mains supplies		N
G.2.4	Battery operation		N
G.3	Determination of telecommunication network transient voltage (V)		N
G.4	Determination of required withstand voltage (V)		N
G.4.1	Mains transients and internal repetitive peaks		N
G.4.2	Transients from telecommunication networks		N
G.4.3	Combination of transients		N
G.4.4	Transients from cable distribution systems		N
G.5	Measurement of transient voltages (V)		N
	a) Transients from a mains supply		N
	For an a.c. mains supply		N
	For a d.c. mains supply		N
	b) Transients from a telecommunication network		N
G.6	Determination of minimum clearances		N

H	ANNEX H, IONIZING RADIATION (see 4.3.13)		N
----------	---	--	---

J	ANNEX J, TABLE OF ELECTROCHEMICAL POTENTIALS (see 2.6.5.6)		N
	Metal(s) used	Considered	--

K	ANNEX K, THERMAL CONTROLS (see 1.5.3 and 5.3.8)		N
K.1	Making and breaking capacity		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
K.2	Thermostat reliability; operating voltage (V) :		N
K.3	Thermostat endurance test; operating voltage (V) :		N
K.4	Temperature limiter endurance; operating voltage (V) :		N
K.5	Thermal cut-out reliability		N
K.6	Stability of operation		N

L	ANNEX L, NORMAL LOAD CONDITIONS FOR SOME TYPES OF ELECTRICAL BUSINESS EQUIPMENT (see 1.2.2.1 and 4.5.2)		P
L.1	Typewriters		N
L.2	Adding machines and cash registers		N
L.3	Erasers		N
L.4	Pencil sharpeners		N
L.5	Duplicators and copy machines		N
L.6	Motor-operated files		N
L.7	Other business equipment		P

M	ANNEX M, CRITERIA FOR TELEPHONE RINGING SIGNALS (see 2.3.1)		N
M.1	Introduction		N
M.2	Method A		N
M.3	Method B		N
M.3.1	Ringling signal		N
M.3.1.1	Frequency (Hz) :		--
M.3.1.2	Voltage (V) :		--
M.3.1.3	Cadence; time (s), voltage (V) :		--
M.3.1.4	Single fault current (mA) :		--
M.3.2	Tripping device and monitoring voltage :		N
M.3.2.1	Conditions for use of a tripping device or a monitoring voltage		N
M.3.2.2	Tripping device		N
M.3.2.3	Monitoring voltage (V) :		N

N	ANNEX N, IMPULSE TEST GENERATORS (see 1.5.7.2, 1.5.7.3, 2.10.3.9, 6.2.2.1, 7.3.2, 7.4.3 and Clause G.5)		N
N.1	ITU-T impulse test generators		N
N.2	IEC 60065 impulse test generator		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
P	ANNEX P, NORMATIVE REFERENCES		--
Q	ANNEX Q, Voltage dependent resistors (VDRs) (see 1.5.9.1)		N
	a) Preferred climatic categories	:	N
	b) Maximum continuous voltage	:	N
	c) Pulse current	:	N
R	ANNEX R, EXAMPLES OF REQUIREMENTS FOR QUALITY CONTROL PROGRAMMES		N
R.1	Minimum separation distances for unpopulated coated printed boards (see 2.10.6.2)		N
R.2	Reduced clearances (see 2.10.3)		N
S	ANNEX S, PROCEDURE FOR IMPULSE TESTING (see 6.2.2.3)		N
S.1	Test equipment		N
S.2	Test procedure		N
S.3	Examples of waveforms during impulse testing		N
T	ANNEX T, GUIDANCE ON PROTECTION AGAINST INGRESS OF WATER (see 1.1.2)		N
U	ANNEX U, INSULATED WINDING WIRES FOR USE WITHOUT INTERLEAVED INSULATION (see 2.10.5.4)		P
V	ANNEX V, AC POWER DISTRIBUTION SYSTEMS (see 1.6.1)		P
V.1	Introduction		P
V.2	TN power distribution systems		P
W	ANNEX W, SUMMATION OF TOUCH CURRENTS		N
W.1	Touch current from electronic circuits		N
W.1.1	Floating circuits		N
W.1.2	Earthed circuits		N
W.2	Interconnection of several equipments		N
W.2.1	Isolation		N
W.2.2	Common return, isolated from earth		N
W.2.3	Common return, connected to protective earth		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
X	ANNEX X, MAXIMUM HEATING EFFECT IN TRANSFORMER TESTS (see clause C.1)		P
X.1	Determination of maximum input current		P
X.2	Overload test procedure	Short circuit performed	P
Y	ANNEX Y, ULTRAVIOLET LIGHT CONDITIONING TEST (see 4.3.13.3)		N
Y.1	Test apparatus		N
Y.2	Mounting of test samples		N
Y.3	Carbon-arc light-exposure apparatus		N
Y.4	Xenon-arc light exposure apparatus		N
Z	ANNEX Z, OVERVOLTAGE CATEGORIES (see 2.10.3.2 and Clause G.2)		P
AA	ANNEX AA, MANDREL TEST (see 2.10.5.8)		N
BB	ANNEX BB, CHANGES IN THE SECOND EDITION		--
CC	ANNEX CC, Evaluation of integrated circuit (IC) current limiters		N
CC.1	General		N
CC.2	Test program 1		N
CC.3	Test program 2		N
DD	ANNEX DD, Requirements for the mounting means of rack-mounted equipment		N
DD.1	General		N
DD.2	Mechanical strength test, variable N.....		N
DD.3	Mechanical strength test, 250N, including end stops.....		N
DD.4	Compliance		N
EE	ANNEX EE, Household and home/office document/media shredders		N
EE.1	General		N
EE.2	Markings and instructions		N
	Use of markings or symbols.....		N
	Information of user instructions, maintenance and/or servicing instructions.....		N
EE.3	Inadvertent reactivation test.....		N

EN 60950-1/Am1			
Clause	Requirement – Test	Result - Remark	Verdict
EE.4	Disconnection of power to hazardous moving parts		N
	Use of markings or symbols.....		N
EE.5	Protection against hazardous moving parts		N
	Test with test finger (Figure 2A)		N
	Test with wedge probe (Figure EE1 and EE2) ...		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict

ATTACHMENT TO TEST REPORT IEC 60950-1 EUROPEAN GROUP DIFFERENCES AND NATIONAL DIFFERENCES Information technology equipment – Safety – Part 1: General requirements			
Differences according to..... : EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Attachment Form No..... : EU_GD_IEC60950_1B_II			
Master Attachment : Date (2011-08)			
Copyright © 2011 IEC System for Conformity Testing and Certification of Electrical Equipment (IECEE), Geneva, Switzerland. All rights reserved.			


EN 60950-1:2006+A11:2009+A1:2010+A12:2011 – CENELEC COMMON MODIFICATIONS

IEC 60950-1, GROUP DIFFERENCES (CENELEC common modifications EN)			
Clause	Requirement – Test	Result - Remark	Verdict
Contents	Add the following annexes: Annex ZA (normative) Annex ZB (normative)	Normative references to international publications with their corresponding European publications Special national conditions	P
General	Delete all the “country” notes in the reference document (IEC 60950-1:2005) according to the following list: 1.4.8 Note 2 1.5.1 Note 2 & 3 1.5.7.1 Note 1.5.8 Note 2 1.5.9.4 Note 1.7.2.1 Note 4, 5 & 6 2.2.3 Note 2.2.4 Note 2.3.2 Note 2.3.2.1 Note 2 2.3.4 Note 2 2.6.3.3 Note 2 & 3 2.7.1 Note 2.10.3.2 Note 2 2.10.5.13 Note 3 3.2.1.1 Note 3.2.4 Note 3. 2.5.1 Note 2 4.3.6 Note 1 & 2 4.7 Note 4 4.7.2.2 Note 4.7.3.1 Note 2 5.1.7.1 Note 3 & 4 5.3.7 Note 1 6 Note 2 & 5 6.1.2.1 Note 2 6.1.2.2 Note 6.2.2 Note 6.2.2.1 Note 2 6.2.2.2 Note 7.1 Note 3 7.2 Note 7.3 Note 1 & 2 G.2.1 Note 2 Annex H Note 2		P
General (A1:2010)	Delete all the “country” notes in the reference document (IEC 60950-1:2005/A1:2010) according to the following list: 1.5.7.1 Note 6.1.2.1 Note 2 6.2.2.1 Note 2 EE.3 Note		P
1.3.Z1	Add the following subclause: 1.3.Z1 Exposure to excessive sound pressure The apparatus shall be so designed and constructed as to present no danger when used for its intended purpose, either in normal operating conditions or under fault conditions,		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	<p>particularly providing protection against exposure to excessive sound pressures from headphones or earphones.</p> <p>NOTE Z1 A new method of measurement is described in EN 50332-1, Sound system equipment: Headphones and earphones associated with portable audio equipment - Maximum sound pressure level measurement methodology and limit considerations - Part 1: General method for “one package equipment”, and in EN 50332-2, Sound system equipment: Headphones and earphones associated with portable audio equipment - Maximum sound pressure level measurement methodology and limit considerations - Part 2: Guidelines to associate sets with headphones coming from different manufacturers.</p>		
(A12:2011)	<p>In EN 60950-1:2006/A12:2011</p> <p>Delete the addition of 1.3.Z1 / EN 60950-1:2006</p> <p>Delete the definition of 1.2.3.Z1 / EN 60950-1:2006/A1:2010</p>		N
1.5.1	<p>Add the following NOTE:</p> <p>NOTE Z1 The use of certain substances in electrical and electronic equipment is restricted within the EU: see Directive 2002/95/EC</p>		N
1.7.2.1 (A1:2010)	<p>In addition, for a PORTABLE SOUND SYSTEM, the instructions shall include a warning that excessive sound pressure from earphones and headphones can cause hearing loss.</p>		N
1.7.2.1 (A12:2011)	<p>In EN 60950-1:2006/A12:2011</p> <p>Delete NOTE Z1 and the addition for Portable Sound System.</p> <p>Add the following clause and annex to the existing standard and amendments.</p>		N
	<p>Zx Protection against excessive sound pressure from personal music players</p>		N
	<p>Zx.1 General</p> <p>This sub-clause specifies requirements for protection against excessive sound pressure from personal music players that are closely coupled to the ear. It also specifies requirements for earphones and headphones intended for use with personal music players.</p> <p>A personal music player is a portable equipment for personal use, that:</p> <p>is designed to allow the user to listen to recorded or broadcast sound or video; and primarily users headphones or earphones that can be worn in or on or around the ear; and allows the user to walk around while in use.</p> <p>NOTE 1 Examples are hand-held or body-worn portable CD players, MP3 audio players, mobile</p>		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	<p>phones with MP3 type features, PDA's or similar equipment.</p> <p>A personal music player and earphones or headphones intended to be used with personal music players shall comply with the requirements of this sub-clause.</p> <p>The requirements in this sub-clause are valid for musci or video mode only.</p> <p>The requirements do not apply:</p> <p>while the personal music player is connected to an external amplifier; or</p> <p>while the headphone or earphones are not used.</p> <p>NOTE 2 An external amplifier is an amplifier which is not part of the personal music player or the listening device, but which is intended to play the music as a standalone music player.</p> <p>The requirements do not apply to:</p> <p>hearing aid equipment and professional equipment;</p> <p>NOTE 3 Professional equipment is equipment sold through special sale s channels. All products sold through normal electronics stores are considered not to professional equipment.</p> <p>analogue personal music players (personal music players without any kind of digital processing of the sound signal) that are brought to the market before the end of 2015.</p>		
	<p>NOTE 4 This exemption has been allowed because this technology is falling out of use and it is expected that within a few years it will no longer exist. This exemption will not be extended to other technologies.</p> <p>For equipment which is clearly designed or intended for use by young children, the limits of EN 71-1 apply.</p>		N
	<p>Zx.2 Equipment requirements</p> <p>No safety provision is required for equipment that complies with the following:</p> <p>equipment provided as a package (personal music player with its listening device), where the acoustic output $L_{Aeq,T}$, is ≤ 85 dBA measured while playing the fixed "programme simulation noise" as described in EN 50332-1; and a personal music player provided with an analogue electrical output socket for a listening device, where the electrical output is ≤ 27 mV measured as described in EN 50332-2, while playing the fixed "programme simulation noise" as described in EN 50332-1.</p> <p>NOTE 1 Wherever the term acoustic acoustic output is used in this clause, the 30 s A-weighted equipment</p>		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	<p>sound pressure level $L_{Aeq,T}$, is meant. See also Zx.5 and Annex Zx. All other equipment shall:</p> <ul style="list-style-type: none"> a) protect the user from unintentional acoustic outputs exceeding those mentioned above; and b) have a standard acoustic output level not exceeding those mentioned above, and automatically return to an output level not exceeding those mentioned above when the power is switched off; and c) provide a means to actively inform the user of the increased sound pressure when the equipment is operated with an acoustic output exceeding those mentioned above. Any means used shall be acknowledged by the user before activating a mode of operation which allows for an acoustic output exceeding those mentioned above. The acknowledgement does not need to be repeated more than once every 20 h of cumulative listening time; and <p>NOTE 2 Examples of means include visual or audible signals. Action from the user is always required. NOTE 3 The 20 h listening time is the accumulative listening time, independent how often and how long the personal music player has been switched off.</p> <ul style="list-style-type: none"> d) have a warning as specified in Zx.3; and e) not exceed the following: <ul style="list-style-type: none"> 1) equipment provided as a package (player with its listening device), the acoustic output shall be ≤ 100 dBA measured while playing the fixed “programme simulation noise” described in EN 50332-1; and 2) a personal music player provided with an analogue electrical output socket for a listening device, the electrical output shall be ≤ 150 mV measured as described in EN 50332-2, while playing the fixed “programme simulation noise” described in EN 50332-1. <p>For music where the average sound pressure (long term $L_{Aeq,T}$) measured over the duration of the song is lower than the average produced by the programme simulation noise, the warning does not need to be given as long as the average sound pressure of the song is below the basic limit of 85 dBA. In this case T becomes the duration of the song.</p> <p>NOTE 4 Classical music typically has an average sound pressure (long term $L_{Aeq,T}$) which is much lower than the average programme simulation noise. Therefore, if the player is capable to analyse the song and compare it with the programme simulation noise, the warning does not need to be given as long as the average sound pressure of the song is below the basic limit of 85 dBA.</p> <p>For example, if the player is set with the programme</p>		

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	simulation noise to 85 dBA, but the average music level of the song is only 65 dBA, there is no need to give a warning or ask an acknowledgement as long as the average sound level of the song is not above the basic limit of 85 dBA.		
	<p>Zx.3 Warning The warning shall be placed on the equipment, or on the packaging, or in the instruction manual and shall consist of the following: the symbol of Figure 1 with a minimum height of 5 mm; and the following wording, or similar: “To prevent possible hearing damage, do not listen at high volume levels for long periods.”</p>  <p>Figure 1 – Warning label (IEC 60417-6044) Alternatively, the entire warning may be given through the equipment display during use, when the user is asked to acknowledge activation of the higher level.</p>		N
	Zx.4 Requirements for listening devices (headphones and earphones)		N
	<p>Zx.4.1 Wired listening devices with analogue input With 94 dBA sound pressure output $L_{Aeq,T}$, the input voltage of the fixed “programme simulation noise” described in EN 50332-2 shall be ≥ 75 mV. This requirement is applicable in any mode where the headphones can operate (active or passive), including any available setting (for example built-in volume level control). NOTE The values of 94 dBA – 75 mV correspond with 85dBA – 27 mV and 100 dBA – 150 mV.</p>		N
	<p>Zx.4.2 Wired listening devices with digital input With any playing device playing the fixed “programme simulation noise” described in EN 50332-1 (and respecting the digital interface standards, where a digital interface standard exists that specifies the equivalent acoustic level), the acoustic output $L_{Aeq,T}$ of the listening device shall be ≤ 100 dBA. This requirement is applicable in any mode where the headphones can operate, including any available setting (for example built-in volume level control, additional sound feature like equalization, etc.). NOTE An example of a wired listening device with</p>		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	digital input is a USB headphone.		
	<p>Zx.4.3 Wireless listening devices In wireless mode: with any playing and transmitting device playing the fixed programme simulation noise described in EN 50332-1; and respecting the wireless transmission standards, where an air interface standard exists that specifies the equivalent acoustic level; and with volume and sound settings in the listening device (for example built-in volume level control, additional sound feature like equalization, etc.) set to the combination of positions that maximize the measured acoustic output for the abovementioned programme simulation noise, the acoustic output LAeq,T of the listening device shall be ≤ 100 dBA. NOTE An example of a wireless listening device is a Bluetooth headphone.</p>		N
	<p>Zx.5 Measurement methods Measurements shall be made in accordance with EN 50332-1 or EN 50332-2 as applicable. Unless stated otherwise, the time interval T shall be 30 s. NOTE Test method for wireless equipment provided without listening device should be defined.</p>		N
2.7.1	<p>Replace the subclause as follows: Basic requirements To protect against excessive current, short-circuits and earth faults in PRIMARY CIRCUITS, protective devices shall be included either as integral parts of the equipment or as parts of the building installation, subject to the following, a), b) and c): a) except as detailed in b) and c), protective devices necessary to comply with the requirements of 5.3 shall be included as parts of the equipment; b) for components in series with the mains input to the equipment such as the supply cord, appliance coupler, r.f.i. filter and switch, short-circuit and earth fault protection may be provided by protective devices in the building installation;</p>		P
	<p>c) it is permitted for PLUGGABLE EQUIPMENT TYPE B or PERMANENTLY CONNECTED EQUIPMENT, to rely on dedicated overcurrent and short-circuit protection in the building installation, provided that the means of protection, e.g. fuses or circuit breakers, is fully specified in the installation instructions. If reliance is placed on protection in the building installation, the installation instructions shall so state, except that for PLUGGABLE EQUIPMENT</p>		P

EN 60950-1:2006+A11:2009+A1:2010+A12:2011											
Clause	Requirement – Test	Result - Remark	Verdict								
	TYPE A the building installation shall be regarded as providing protection in accordance with the rating of the wall socket outlet.										
2.7.2	This subclause has been declared 'void'.		N								
3.2.3	Delete the NOTE in Table 3A, and delete also in this table the conduit sizes in parentheses.		N								
3.2.5.1	<p>Replace "60245 IEC 53" by "H05 RR-F"; "60227 IEC 52" by "H03 VV-F or H03 VVH2-F"; "60227 IEC 53" by "H05 VV-F or H05 VVH2-F2".</p> <p>In Table 3B, replace the first four lines by the following:</p> <table style="margin-left: 40px;"> <tr> <td>Up to and including 6 </td> <td>0,75^{a)} </td> </tr> <tr> <td>Over 6 up to and including 10 </td> <td>(0,75)^{b)} 1,0 </td> </tr> <tr> <td>Over 10 up to and including 16 </td> <td>(1,0)^{c)} 1,5 </td> </tr> <tr> <td> </td> <td></td> </tr> </table> <p>In the conditions applicable to Table 3B delete the words "in some countries" in condition^{a)}.</p> <p>In NOTE 1, applicable to Table 3B, delete the second sentence.</p>	Up to and including 6	0,75 ^{a)}	Over 6 up to and including 10	(0,75) ^{b)} 1,0	Over 10 up to and including 16	(1,0) ^{c)} 1,5				N
Up to and including 6	0,75 ^{a)}										
Over 6 up to and including 10	(0,75) ^{b)} 1,0										
Over 10 up to and including 16	(1,0) ^{c)} 1,5										
3.3.4	<p>In Table 3D, delete the fourth line: conductor sizes for 10 to 13 A, and replace with the following:</p> <table style="margin-left: 40px;"> <tr> <td>Over 10 up to and including 16 </td> <td>1,5 to 2,5 </td> <td>1,5 to 4 </td> </tr> </table> <p>Delete the fifth line: conductor sizes for 13 to 16 A</p>	Over 10 up to and including 16	1,5 to 2,5	1,5 to 4		N					
Over 10 up to and including 16	1,5 to 2,5	1,5 to 4									
4.3.13.6 (A1:2010)	<p>Replace the existing NOTE by the following:</p> <p>NOTE Z1 Attention is drawn to:</p> <p>1999/519/EC: Council Recommendation on the limitation of exposure of the general public to electromagnetic fields 0 Hz to 300 GHz, and</p> <p>2006/25/EC: Directive on the minimum health and safety requirements regarding the exposure of workers to risks arising from physical agents (artificial optical radiation).</p>		N								
	Standards taking into account mentioned Recommendation and Directive which demonstrate compliance with the applicable EU Directive are indicated in the OJEC.		N								
Annex H	<p>Replace the last paragraph of this annex by:</p> <p>At any point 10 cm from the surface of the OPERATOR ACCESS AREA, the dose rate shall not exceed 1 µSv/h (0,1 mR/h) (see NOTE). Account is taken of the background level.</p> <p>Replace the notes as follows:</p>		N								

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	NOTE These values appear in Directive 96/29/Euratom. Delete NOTE 2.		
Bibliography	Additional EN standards.		—

ZA	NORMATIVE REFERENCES TO INTERNATIONAL PUBLICATIONS WITH THEIR CORRESPONDING EUROPEAN PUBLICATIONS	—
-----------	--	---

ZB ANNEX (normative) SPECIAL NATIONAL CONDITIONS (EN)			
Clause	Requirement – Test	Result - Remark	Verdict
1.2.4.1	In Denmark , certain types of Class I appliances (see 3.2.1.1) may be provided with a plug not establishing earthing conditions when inserted into Danish socket-outlets.		N
1.2.13.14	In Norway and Sweden , for requirements see 1.7.2.1 and 7.3 of this annex.		N
1.5.7.1	In Finland, Norway and Sweden , resistors bridging BASIC INSULATION in CLASS I PLUGGABLE EQUIPMENT TYPE A must comply with the requirements in 1.5.7.1. In addition when a single resistor is used, the resistor must withstand the resistor test in 1.5.7.2.		N
1.5.8	In Norway , due to the IT power system used (see annex V, Figure V.7), capacitors are required to be rated for the applicable line-to-line voltage (230 V).		N
1.5.9.4	In Finland, Norway and Sweden , the third dashed sentence is applicable only to equipment as defined in 6.1.2.2 of this annex.		N
1.7.2.1	In Finland, Norway and Sweden , CLASS I PLUGGABLE EQUIPMENT TYPE A intended for connection to other equipment or a network shall, if safety relies on connection to protective earth or if surge suppressors are connected between the network terminals and accessible parts, have a marking stating that the equipment must be connected to an earthed mains socket-outlet. The marking text in the applicable countries shall be as follows: In Finland: "Laite on liitettävä suojakoskettimilla varustettuun pistorasiaan" In Norway: "Apparatet må tilkoples jordet stikkontakt" In Sweden: "Apparaten skall anslutas till jordat uttag" In Norway and Sweden , the screen of the cable		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
	<p>distribution system is normally not earthed at the entrance of the building and there is normally no equipotential bonding system within the building. Therefore the protective earthing of the building installation need to be isolated from the screen of a cable distribution system.</p> <p>It is however accepted to provide the insulation external to the equipment by an adapter or an interconnection cable with galvanic isolator, which may be provided by e.g. a retailer.</p> <p>The user manual shall then have the following or similar information in Norwegian and Swedish language respectively, depending on in what country the equipment is intended to be used in:</p> <p>“Equipment connected to the protective earthing of the building installation through the mains connection or through other equipment with a connection to protective earthing – and to a cable distribution system using coaxial cable, may in some circumstances create a fire hazard. Connection to a cable distribution system has therefore to be provided through a device providing electrical isolation below a certain frequency range (galvanic isolator, see EN 60728-11).”</p>		
	<p>NOTE In Norway, due to regulation for installations of cable distribution systems, and in Sweden, a galvanic isolator shall provide electrical insulation below 5 MHz. The insulation shall withstand a dielectric strength of 1,5 kV r.m.s., 50 Hz or 60 Hz, for 1 min.</p> <p>Translation to Norwegian (the Swedish text will also be accepted in Norway):</p> <p>“Utstyr som er koplet til beskyttelsesjord via nettplugg og/eller via annet jordtilkøpet utstyr – og er tilkøpet et kabel-TV nett, kan forårsake brannfare. For å unngå dette skal det ved tilkøpling av utstyret til kabel-TV nettet installeres en galvanisk isolator mellom utstyret og kabel-TV nettet.”</p> <p>Translation to Swedish:</p> <p>”Utrustning som är kopplad till skyddsjord via jordat vägguttag och/eller via annan utrustning och samtidigt är kopplad till kabel-TV nät kan i vissa fall medföra risk för brand. För att undvika detta skall vid anslutning av utrustningen till kabel-TV nät galvanisk isolator finnas mellan utrustningen och kabel-TV nätet.”</p>		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
1.7.5	In Denmark , socket-outlets for providing power to other equipment shall be in accordance with the Heavy Current Regulations, Section 107-2-D1, Standard Sheet DK 1-3a, DK 1-5a or DK 1-7a, when used on Class I equipment. For STATIONARY EQUIPMENT the socket-outlet shall be in accordance with Standard Sheet DK 1-1b or DK 1-5a. For CLASS II EQUIPMENT the socket outlet shall be in accordance with Standard Sheet DKA 1-4a.		N
2.2.4	In Norway , for requirements see 1.7.2.1, 6.1.2.1 and 6.1.2.2 of this annex.		N
2.3.2	In Finland, Norway and Sweden there are additional requirements for the insulation. See 6.1.2.1 and 6.1.2.2 of this annex.		N
2.3.4	In Norway , for requirements see 1.7.2.1, 6.1.2.1 and 6.1.2.2 of this annex.		N
2.6.3.3	In the United Kingdom , the current rating of the circuit shall be taken as 13 A, not 16 A.		P
2.7.1	In the United Kingdom , to protect against excessive currents and short-circuits in the PRIMARY CIRCUIT of DIRECT PLUG-IN EQUIPMENT, tests according to 5.3 shall be conducted, using an external protective device rated 30 A or 32 A. If these tests fail, suitable protective devices shall be included as integral parts of the DIRECT PLUG-IN EQUIPMENT, so that the requirements of 5.3 are met.		N
2.10.5.13	In Finland, Norway and Sweden , there are additional requirements for the insulation, see 6.1.2.1 and 6.1.2.2 of this annex.		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
3.2.1.1	<p>In Switzerland, supply cords of equipment having a RATED CURRENT not exceeding 10 A shall be provided with a plug complying with SEV 1011 or IEC 60884-1 and one of the following dimension sheets:</p> <p>SEV 6532-2.1991 Plug Type 15 3P+N+PE 250/400 V, 10 A</p> <p>SEV 6533-2.1991 Plug Type 11 L+N 250 V, 10 A</p> <p>SEV 6534-2.1991 Plug Type 12 L+N+PE 250 V, 10 A</p> <p>In general, EN 60309 applies for plugs for currents exceeding 10 A. However, a 16 A plug and socket-outlet system is being introduced in Switzerland, the plugs of which are according to the following dimension sheets, published in February 1998:</p> <p>SEV 5932-2.1998: Plug Type 25 , 3L+N+PE 230/400 V, 16 A</p> <p>SEV 5933-2.1998: Plug Type 21, L+N, 250 V, 16A</p> <p>SEV 5934-2.1998: Plug Type 23, L+N+PE 250 V, 16 A</p>		N
3.2.1.1	<p>In Denmark, supply cords of single-phase equipment having a rated current not exceeding 13 A shall be provided with a plug according to the Heavy Current Regulations, Section 107-2-D1.</p> <p>CLASS I EQUIPMENT provided with socket-outlets with earth contacts or which are intended to be used in locations where protection against indirect contact is required according to the wiring rules shall be provided with a plug in accordance with standard sheet DK 2-1a or DK 2-5a.</p> <p>If poly-phase equipment and single-phase equipment having a RATED CURRENT exceeding 13 A is provided with a supply cord with a plug, this plug shall be in accordance with the Heavy Current Regulations, Section 107-2-D1 or EN 60309-2.</p>		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
3.2.1.1	<p>In Spain, supply cords of single-phase equipment having a rated current not exceeding 10 A shall be provided with a plug according to UNE 20315:1994.</p> <p>Supply cords of single-phase equipment having a rated current not exceeding 2,5 A shall be provided with a plug according to UNE-EN 50075:1993.</p> <p>CLASS I EQUIPMENT provided with socket-outlets with earth contacts or which are intended to be used in locations where protection against indirect contact is required according to the wiring rules, shall be provided with a plug in accordance with standard UNE 20315:1994.</p> <p>If poly-phase equipment is provided with a supply cord with a plug, this plug shall be in accordance with UNE-EN 60309-2.</p>		N
3.2.1.1	<p>In the United Kingdom, apparatus which is fitted with a flexible cable or cord and is designed to be connected to a mains socket conforming to BS 1363 by means of that flexible cable or cord and plug, shall be fitted with a 'standard plug' in accordance with Statutory Instrument 1768:1994 - The Plugs and Sockets etc. (Safety) Regulations 1994, unless exempted by those regulations.</p> <p>NOTE 'Standard plug' is defined in SI 1768:1994 and essentially means an approved plug conforming to BS 1363 or an approved conversion plug.</p>		N
3.2.1.1	<p>In Ireland, apparatus which is fitted with a flexible cable or cord and is designed to be connected to a mains socket conforming to I.S. 411 by means of that flexible cable or cord and plug, shall be fitted with a 13 A plug in accordance with Statutory Instrument 525:1997 - National Standards Authority of Ireland (section 28) (13 A Plugs and Conversion Adaptors for Domestic Use) Regulations 1997.</p>		N
3.2.4	<p>In Switzerland, for requirements see 3.2.1.1 of this annex.</p>		N
3.2.5.1	<p>In the United Kingdom, a power supply cord with conductor of 1,25 mm² is allowed for equipment with a rated current over 10 A and up to and including 13 A.</p>		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
3.3.4	In the United Kingdom , the range of conductor sizes of flexible cords to be accepted by terminals for equipment with a RATED CURRENT of over 10 A up to and including 13 A is: • 1,25 mm ² to 1,5 mm ² nominal cross-sectional area.		N
4.3.6	In the United Kingdom , the torque test is performed using a socket outlet complying with BS 1363 part 1:1995, including Amendment 1:1997 and Amendment 2:2003 and the plug part of DIRECT PLUG-IN EQUIPMENT shall be assessed to BS 1363: Part 1, 12.1, 12.2, 12.3, 12.9, 12.11, 12.12, 12.13, 12.16 and 12.17, except that the test of 12.17 is performed at not less than 125 °C. Where the metal earth pin is replaced by an Insulated Shutter Opening Device (ISOD), the requirements of clauses 22.2 and 23 also apply.		N
4.3.6	In Ireland , DIRECT PLUG-IN EQUIPMENT is known as plug similar devices. Such devices shall comply with Statutory Instrument 526:1997 - National Standards Authority of Ireland (Section 28) (Electrical plugs, plug similar devices and sockets for domestic use) Regulations, 1997.		N
5.1.7.1	In Finland, Norway and Sweden TOUCH CURRENT measurement results exceeding 3,5 mA r.m.s. are permitted only for the following equipment: • STATIONARY PLUGGABLE EQUIPMENT TYPE A that is intended to be used in a RESTRICTED ACCESS LOCATION where equipotential bonding has been applied, for example, in a telecommunication centre; and has provision for a permanently connected PROTECTIVE EARTHING CONDUCTOR; and is provided with instructions for the installation of that conductor by a SERVICE PERSON; • STATIONARY PLUGGABLE EQUIPMENT TYPE B; • STATIONARY PERMANENTLY CONNECTED EQUIPMENT.		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
6.1.2.1 (A1:2010)	<p>In Finland, Norway and Sweden, add the following text between the first and second paragraph of the compliance clause:</p> <p>If this insulation is solid, including insulation forming part of a component, it shall at least consist of either</p> <ul style="list-style-type: none"> - two layers of thin sheet material, each of which shall pass the electric strength test below, or - one layer having a distance through insulation of at least 0,4 mm, which shall pass the electric strength test below. <p>Alternatively for components, there is no distance through insulation requirements for the insulation consisting of an insulating compound completely filling the casing, so that CLEARANCES and CREEPAGE DISTANCES do not exist, if the component passes the electric strength test in accordance with the compliance clause below and in addition</p> <ul style="list-style-type: none"> - passes the tests and inspection criteria of 2.10.11 with an electric strength test of 1,5 kV multiplied by 1,6 (the electric strength test of 2.10.10 shall be performed using 1,5 kV), and - is subject to ROUTINE TESTING for electric strength during manufacturing, using a test voltage of 1,5 kV. 		N
	<p>It is permitted to bridge this insulation with an optocoupler complying with 2.10.5.4 b).</p> <p>It is permitted to bridge this insulation with a capacitor complying with EN 60384-14:2005, subclass Y2.</p> <p>A capacitor classified Y3 according to EN 60384-14:2005, may bridge this insulation under the following conditions:</p> <ul style="list-style-type: none"> - the insulation requirements are satisfied by having a capacitor classified Y3 as defined by EN 60384-14, which in addition to the Y3 testing, is tested with an impulse test of 2,5 kV defined in EN 60950-1:2006, 6.2.2.1; - the additional testing shall be performed on all the test specimens as described in EN 60384-14; - the impulse test of 2,5 kV is to be performed before the endurance test in EN 60384-14, in the sequence of tests as described in EN 60384-14. 		N

EN 60950-1:2006+A11:2009+A1:2010+A12:2011			
Clause	Requirement – Test	Result - Remark	Verdict
6.1.2.2	In Finland, Norway and Sweden , the exclusions are applicable for PERMANENTLY CONNECTED EQUIPMENT, PLUGGABLE EQUIPMENT TYPE B and equipment intended to be used in a RESTRICTED ACCESS LOCATION where equipotential bonding has been applied, e.g. in a telecommunication centre, and which has provision for a permanently connected PROTECTIVE EARTHING CONDUCTOR and is provided with instructions for the installation of that conductor by a SERVICE PERSON.		N
7.2	In Finland, Norway and Sweden , for requirements see 6.1.2.1 and 6.1.2.2 of this annex. The term TELECOMMUNICATION NETWORK in 6.1.2 being replaced by the term CABLE DISTRIBUTION SYSTEM.		N
7.3	In Norway and Sweden , for requirements see 1.2.13.14 and 1.7.2.1 of this annex.		N
7.3	In Norway , for installation conditions see EN 60728-11:2005.		N

Test Tables

1.5.1	TABLE: List of critical components				P
Object/part No.	Manufacturer/ trademark	Type/model	Technical data	Standard (Edition/ year)	Mark(s) of conformity ¹⁾
Enclosure	Various	Various	V-0, 115°C	UL 94 UL 746	UL
PCB	Various	YCF-120W	CAM1 150°C	UL 94; UL 746	UL
Insulation sheet	Mianyang Longhua Film Co., Ltd.	PC2860	V-0, 130°C, Min. thick: 0.4mm	UL 94	UL
AC inlet	NINGTEKE Electronic Co.Ltd	ROCKE-13C	AC300V 10A 105°C,	--	UL
Protective Bonding conductor	JIAN DA Electronic Co., Ltd.	1015	Min. 300V 20AWG 105°C	UL 758	UL
Fuse (F1)	HONG DA Electronic Co., Ltd.	ICP-SERIES	AC250V, 5.0A	EN 60127-1 EN 60127-2	VDE
Bridge Rectifier (BD1)	JIN HONG Electronic Co., Ltd.	KBU808	Min.4A, min. 600V	EN 60950-1	Test with appliance
X2-Cap. CX1	JIMSON	MKP	0.33uF K/275V	EN 60384-14	UL VDE
Electrical Cap	Various	Various	120UF/400V 105°C	EN 60950-1	Test with appliance
Mosefet(Q1)	Various	Various	FQPY 10A 600V	EN 60950-1	Test with appliance
CY4	SONGTIAN Electronic Co., Ltd.	222M 400V	AC400V2200P F	EN 60384-14	UL VDE
CY1, CY2, CY3	SONGTIAN Electronic Co., Ltd.	102M 400V	AC250V1000P F	EN 60384-14	UL VDE
Opto-coupler (IC2)	JUZH I YING Electronic Co., Ltd.	EL817C	100°C	EN 60950-1 EN 60747-5-2	VDE
Transformer	HUI SHUN Electronic Co., Ltd.	CE6019380 POT3319	Class B	EN 60950-1	UL
- Bobbin	TAIWANHEJIN PLSAYICS.CO., LTD.	POT3319	U-94V	UL 94	UL
- Secondary triple insulated wire	DAH JIN TECHNOLOGY CO., LTD.	0.4MM*6	130°C	UL 2353	UL
- Magnet wire	PACIFIC ELECTRONICS WIRE&CABLE CO., LTD.	2UEW	130°C	UL 1446	UL
-Teflon tube	JIANGYIN HUAYUE ELECTRICAL MATERIAL CO.LTD	TFT, TFS	130°C	UL 1446	UL
-Insulation tape	JINGYING JUNDA PLASAYICS CO.LTD	PZ280	130°C	UL 510	UL
-Varnish	TAIHU HUAGONG CO.LTD	ET-90 T-4260	100°C	UL 224	UL
Output wire	WEILIN Electronic Co., Ltd.	2725	80°C, 30V, VW-1	UL 758	UL

¹⁾ An asterisk indicates a mark which assures the agreed level of surveillance.

Test Tables

1.6.2	TABLE: electrical data test (in normal conditions)						P
fuse #	I rated (A)	U (V)	P (W)	I (A)	Ifuse (A)	condition	
F1	--	90V, 50Hz	150.6	2.461	2.461	Loading 12V, 10A.	
F1	2	100V, 50Hz	148.5	2.163	2.163	Loading 12V, 10A.	
F1	2	240V, 50Hz	144.0	1.015	1.015	Loading 12V, 10A.	
F1	--	264V, 50Hz	144.3	0.919	0.919	Loading 12V, 10A.	
F1	--	90V, 60Hz	149.9	2.366	2.366	Loading 12V, 10A.	
F1	--	100V, 60Hz	147.3	2.086	2.086	Loading 12V, 10A.	
F1	--	240V, 60Hz	136.8	0.932	0.932	Loading 12V, 10A.	
F1	--	264V, 60Hz	144.2	0.879	0.879	Loading 12V, 10A.	
Remark:							

2.1.1.5 c) 1)	TABLE: Max. V, A, VA test				N
Voltage (rated) (V)	Current (rated) (A)	Voltage (max.) (V)	Current (max.) (A)	VA (max.) (VA)	
12	10	12.1	17.9	211.3	
Supplementary information:					

2.1.1.5 c) 2)	TABLE: Stored energy		N
Capacitance C (µF)	Voltage U (V)	Energy E (J)	
--	--	--	
Supplementary information:			

2.2	TABLE: evaluation of voltage limiting components in SELV circuits				P
Location	Voltage measurement (V)		Comments		
Component (measured between)		max. voltage (V) (normal operation)		Voltage Limiting Components	
Transformer	Location	V peak	V d.c.		
T1	Pin 9/10/11-12/13/14		65.0	--	--
	After D3		--	31.0	D3
Fault test performed on voltage limiting components		Voltage measured (V) in SELV circuits (V peak or V d.c.)			
D3 short circuit		0			

Test Tables

Remark:

2.5	TABLE: Limited power source measurement				N
Condition	Output voltage (Uoc) (V)	Output current (Isc) (A)		Apparent power (S) (VA)	
Normal condition	--	--		--	
Single fault		I _{sc} (A)		VA	
		Meas.	Limit	Meas.	Limit
--	--	--	--	--	--
Supplementary information: SC=Short circuit, OC=Open circuit					

2.10.2	TABLE: Working voltage measurement					P
Component	From	To	V peak	V rms	Remark	
T1	Pin1	Pin9/10/11	396	238		
		Pin12/13/14	376	234		
		PE	376	234		
	Pin2/3	Pin9/10/11	376	233		
		Pin12/13/14	432	238		
		PE	432	238		
	Pin4	Pin9/10/11	560	270		
		Pin12/13/14	588	290	Max. Vpeak and Vrms	
		PE	588	290		
	Pin6	Pin9/10/11	412	219		
		Pin12/13/14	352	217		
		PE	352	216		
	Pin7/8	Pin9/10/11	388	238		
		Pin12/13/14	376	238		
		PE	376	238		
IC2	Pin1	Pin3	372	232		
		Pin4	376	230		
		Pin2	372	230		
		Pin4	372	228		
CY4	Primary	Secondary	376	234		
Remark:						

Test Tables

2.10.3 and 2.10.4	TABLE: Clearance and creepage distance measurements						P
Clearance (cl) and creepage distance (cr) at/of/between:	U peak (V)	U r.m.s. (V)	Required cl (mm)	cl (mm)	Required cr (mm)	cr (mm)	
Functional:							
L to N	339	240	1.5	4.5	2.4	4.5	
Basic:							
Two terminals between F1	339	240	2.0	2.1	2.4	2.1	
L to PE	339	240	2.0	5.8	2.4	5.8	
N to PE	339	240	2.0	3.7	2.4	3.7	
Reinforced							
Pri. to Sec. under IC2	376	240	4.0	7.0	4.8	7.0	
Pri. to Sec. under T1	588	290	4.6	>10	5.8	>10	
T1 Sec. winding to core	588	290	4.6	8.0	5.8	8.0	
Pri. to enclosure	339	240	4.0	6.0	4.8	6.0	
Supplementary information:							

2.10.5	TABLE: Distance through insulation measurements					P
distance through insulation di at/of:	U peak (V)	U rms (V)	Test voltage (V)	Required DTI (mm)	DTI (mm)	
Enclosure	339	240	3000	Min. 0.4	2.2	
Opto-coupler(IC2)	339	240	3000	0.4	Min. 0.4	
Bobbin of transformer(T1)	588	290	3000	0.4	Min. 0.4	
Remark:						

4.3.8	TABLE: Batteries								N
The tests of 4.3.8 are applicable only when appropriate battery data is not available								N	
Is it possible to install the battery in a reverse polarity position?								N	
Non-rechargeable batteries				Rechargeable batteries					
Discharging		Un-intentional charging	Charging		Discharging		Reversed charging		
Meas. current	Manuf. Specs.		Meas. current	Manuf. Specs.	Meas. current	Manuf. Specs.	Meas. current	Manuf. Specs.	

Test Tables

Max. current during normal condition	--	--	--	--	--	--	--	--	--
Max. current during fault condition	--	--	--	--	--	--	--	--	--
Test results:									
- Chemical leaks								Verdict	
								N	
- Explosion of the battery								N	
- Emission of flame or expulsion of molten metal								N	
- Electric strength tests of equipment after completion of tests								N	
Supplementary information:									

4.5	TABLE: Thermal requirements					P
	Supply voltage (V)	90V 50Hz ¹⁾	264V 60Hz ²⁾	90V 50Hz ³⁾	264V 60Hz ⁴⁾	—
	Ambient T _{min} (°C)	40	40	40	40	—
	Ambient T _{max} (°C)	40	40	40	40	—
	Maximum measured temperature T of part/at::	T (°C)				Allowed T _{max} (°C)
	AC inlet	77.4	68.4	73.9	65.3	85
	MOV1 body	72.1	64.8	68.5	62.4	85
	X-cap(CX1)	88.7	80.6	85.7	89.2	100
	TL1 winding	86.3	78.6	84.9	76.6	130
	X-cap(CX2)	89.9	84.6	86.7	82.3	100
	TL2 winding	91.2	85.8	90.3	83.9	130
	PCB under BD1	105.2	91.1	103.2	86.8	130
	Body of bulk cap. C1	98.8	86.7	95.6	83.9	105
	Heatsink of Q1(considered as PCB)	101.3	90.5	97.6	89.4	130
	CY4 body	71.5	57.3	74.7	60.1	125
	T1 winding	98.9	95.2	96.4	93.7	110
	T1 core	91.1	88.1	90.3	87.4	110
	Body of IC2 (Opto-coupler)	98.9	94.1	96.4	91.2	100
	L2 winding	88.3	72.2	85.6	67.2	130
	Heatsink of D3(considered as PCB)	106.6	105.8	102.4	103.7	130
	Body of bulk cap. C12	101.1	99.9	97.0	95.7	105
	Output wire	68.4	60.9	65.5	59.5	80

Test Tables

Inside enclosure (Top T1)	80.0	72.1	74.3	70.1	95		
Outside enclosure (Top T1)	72.3	66.6	68.9	64.5	95		
Supplementary information:							
Temperature T of winding:	t ₁ (°C)	R ₁ (Ω)	t ₂ (°C)	R ₂ (Ω)	T (°C)	Allowed T _{max} (°C)	Insulation class
--	--	--	--	--	--	--	--
Supplementary information: 1), 2): Label downwards; 3), 4): Label upwards							

4.5.5	TABLE: Ball pressure test of thermoplastics			N
	Required impression diameter (mm)	≤ 2 mm		---
Part		Test temperature (°C)	Impression diameter (mm)	
--		--	--	
Supplementary information:				

4.7	TABLE: Resistance to fire				P
Part	Manufacturer of material	Type of material	Thickness (mm)	Flammability class	Evidence
Transformer bobbin	TAIWANHEJIN PLSAYICS.CO., LTD.	POT3319	0.7	V-0	UL
Enclosure	Various	Various	2.0	V-0	UL
PCB	Various	YCF-120W	1.6	V-0	UL
Supplementary information:					

5.1.6	TABLE: Touch current measurement				P
Condition	L → terminal A (mA)	N → terminal A (mA)	Limit (mA)	Comments	
L&N to enclosure	0.18	0.18	3.5	--	
Supplementary information: Output terminal “-” connected to PE.					

5.2	TABLE: Electric strength tests, impulse tests and voltage surge tests			P
Test voltage applied between:		Voltage shape (AC, DC, impulse, surge)	Test voltage (V)	Breakdown Yes / No
L/N to output		AC	3000	No
L/N to enclosure with metal foil		AC	1893	No
Transformer T1: Primary and secondary		AC	3000	No

Test Tables

Transformer T1: secondary and core	AC	3000	No
One layer of insulation tape	AC	3000	No
Insulation sheet	AC	3000	No
Supplementary information:			

5.3.5		TABLE: Fault condition tests					P
		ambient temperature (°C)			40		--
		model/type of power supply			See below		--
		manufacturer of power supply			See page 1		--
		rated markings of power supply			See rating label		--
No.	component No.	fault	test voltage (V)	test time	fuse No.	fuse current (A)	result
1	Output	Overload	240	6h	F1	12→1.2 14→1.4 16→1.6 16.2→0.05	Overload current is 16A, and ran for thermal equilibrium under it. When loaded over 16A and ran about 30minutes, unit protected. No damaged, no hazard. T1 winding: 132.2°C
2	Output	Short circuit	240	10min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
3	T1 Pin 9/10/11-12/13/14	Short circuit	240	30min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
4	T1 Pin1-2/3	Short circuit	240	30min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
5	T1 Pin6-7/8	Short circuit	240	30min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
6	IC2 pin1-2	Short circuit	240	10min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
7	IC2 pin3-4	Short circuit	240	10min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
8	Q1 Pin G-S	Short circuit	240	10min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.

Test Tables

9	Q1 Pin D-S	Short circuit	240	5min	F1	0.05	Unit shutdown after short, Fuse F1 opened. Q1, BD1, R1, R1 damaged. No hazards
10	Q1 Pin G-D	Short circuit	240	5min	F1	0.05	Unit shutdown after short, Fuse F1 opened. Q1, BD1, R1, R2, damaged. No hazards
11	BD1	Short circuit	240	5min	F1	0	Unit shutdown after short, Fuse F1 opened. BD1 damaged. No hazards
12	R13	Short circuit	240	10min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
13	R17	Short circuit	240	10min	F1	0.05	Unit shutdown after short, recoverable when fault removed. No damaged, no hazards.
14	C1	Short circuit	240	5min	F1	0	Unit shutdown after short, Fuse F1 opened. BD1 damaged. No hazards
<p>Remark:</p> <ol style="list-style-type: none"> 1) SELV output did not exceed 42.4Vpeak or 60Vdc for longer than 0.2 secs and did not exceed the limit of 71Vpeak or 120Vdc after abnormal tests were applied. 2) The electric strength tests were successfully conducted after completion of fault. 3) Temperature limit for transformer winding is 165°C. 							

Photos



Photos



Photos

